

KEY FOB PROGRAMMING INSTRUCTIONS - 10335583

FOR AUTOMOBILES:

These vehicles can be programmed using the instructions below:

- 2001-2005 Chevrolet Venture
- 2001-2004 Oldsmobile Silhouette
- 2001-2005 Pontiac Montana

These vehicles require the use of a professional scan tool for programming (see your local GM dealer or ACDelco Professional Service Center):

- 2004-2012 Chevrolet Colorado
- 2004-2012 GMC Canyon
- 2006-2010 Hummer H3
- 2009-2010 Hummer H3T

PROGRAMMING INSTRUCTIONS

⚠ IMPORTANT: ALL TRANSMITTERS WHICH ARE TO BE RECOGNIZED BY THE REMOTE CONTROL DOOR LOCK RECEIVER (RCDLR) MUST BE PROGRAMMED IN A SINGLE PROGRAMMING SEQUENCE. IF THE SYSTEM IS PLACED IN PROGRAM MODE IT WILL ERASE ALL PREVIOUSLY PROGRAMMED TRANSMITTERS UPON THE RECEIPT OF THE PROGRAMMING SIGNAL FROM THE FIRST TRANSMITTER. UP TO FOUR TRANSMITTERS CAN BE PROGRAMMED. TO PREVENT THE PROGRAMMING OF TRANSMITTERS TO AN INCORRECT VEHICLE, DO NOT OPERATE OR PROGRAM THE TRANSMITTERS IN THE VICINITY OF OTHER VEHICLES THAT ARE IN THE KEYLESS ENTRY PROGRAM MODE.

1. Remove the ignition key from the ignition lock cylinder.
2. Remove the body control module (BCM) PRGRM fuse from the fuse block. (Refer to "Instrument Panel Fuse Block" in your Owner's Manual for the location of your fuse block and the Fuse Usage Chart.)
3. Close all of the doors.
4. Insert the ignition key into the ignition lock cylinder.
5. Turn the ignition to ACC.
6. Turn the ignition to OFF, and then back to ACC within 1 second.
7. Open and then close any vehicle door. The vehicle will chime in order to confirm that the programming mode has been entered.
8. Press and hold the transmitter LOCK and UNLOCK buttons simultaneously for approximately 14 seconds.

⚠ IMPORTANT: AFTER APPROXIMATELY 3-5 SECONDS THE VEHICLE WILL CHIME ONCE TO CONFIRM THAT THE PROGRAMMING HAS BEEN COMPLETED FOR THAT TRANSMITTER.

9. Repeat the previous step in order to program each additional transmitter.
10. Remove the ignition key from the ignition lock cylinder.
11. Install the BCM PRGRM fuse into the fuse block.
12. Operate the functions of each transmitter in order to verify correct system operation.